



Thermal Field in a NMR Cryostat

Annunziata D'Orazio Agostini Chiara Simone Fiacco



Overall Objective of Research Program

The main objective of the present work was to study the thermal field inside the cryostat:

- 1) developing three different models of cryostat with particular reference to the type of closures placed at the ends.
- 2) considering insulation and boundary conditions able to simulate the effect of a "cold head" placed in contact with a very limited portion of the cryo-shields.
- 3) considering tie rods mounted in real cryostat to maintain the empty cavity and to center the magnetic field.

OUTLINE

Introduction

■ Modelling Using Comsol Multiphysics

Results

Conclusions

NMR Superconducting Magnet

- ■Advantages
 - Homogeneous, stable and high static field
 - ❖Possibility to disable the power to the magnet
 - Excellent diagnostic image
- Disadvantages
 - *****Expensive
 - High residual external field (require shielding)
 - Maintaining cryogenic temperatures
 - Quench risk

Structure of cryostat

- □ Concentric structure
 coaxial with the
 superconducting windings
 to avoid helium
 evaporation
- □ Composed by:
 - Magnet immersed in liquid helium at 4 K
 - Radiative shields
 - Cold head




Figure 1: Cryostat's scheme with cryo-shields and cold head

Real Cryostat




Figure 2: Front view of a real cryostat



Figure 3: Concetric vessels


Simplified geometry of Cryostat


- □ At the beginning a very simplified model of cryostat constited of open concentric cylinders spaced from vacuum zones has been developed.
- This model no take into account the thermal field near the closures simulating only the heat exchange in the central part of the cryostat.




Model of Cryostat with closures

□ A more realistic model has been developed to investigate the thermal field near the closures. More specifically, three different geometries with particular reference to the type of closures placed at the ends have been implemented.







Geometry with flat closures

Geometry with inclined closures

Geometry with rounded closures


Mesh

☐ Swept mesh with elements of different sizes :

Closures:

Maximum element size 0.1 m


❖Cylinders:
Maximum element
size: 0.2 m



Materials

	Type of material	<u>ρ</u> (kg/m3)	Thermal conductivity [W/m K]	Specific Heat [J/K. kg]
Outer vessel	304 Stainless Steel	7999.5	Variable with Temperature	Variable with Temperature
Radiative Shields	6063 – T5 Aluminum	2712.6	Variable with Temperature	Variable with Temperature
Inner vessel	304 Stainless Steel	7999.5	Variable with Temperature	Variable with Temperature
Cold head	OFHC Copper	8940	Variable with Temperature	Variable with Temperature

Numerical study of the thermal field



ρ	density(SI unit: kg/m3)
Ср	specific heat capacity at constant pressure (SI unit: $J/(kg \cdot K)$)
Т	absolute temperature (SI unit: K)
u	velocity vector (SI unit: m/s)

Boundary condition


- ☐Heat flux
- □ Radiation Surface to ambient:
- ☐ Radiation Surface to Surface
- □ Specified temperature
- ☐Specified inward heat flux

Initial conditions:

- ➤ External Temperature=293.15 K
- ➤ Internal temeperature: 4.2 K

Heat convective transfer coefficients (1)


- Helium
 - Liquid
 - Vapor
- Air
- External cylinder
- Internal cylinder
- Vertical wall




Heat convective transfer coefficients (2)

External steel vessel

$$h_{ext}=2.13\frac{W}{m^2K}$$





➤ Heat flux

$$-n \cdot (k\nabla T) = h_{ext}(T_{ext} - T)$$

 $q = k \cdot \nabla T$ conductive heat flux vector $\left[\frac{W}{m^2}\right]$

 \imath normal vector of the boundary

 h_{ext} heat transfer coefficient

> Heat flux

$$-n \cdot (k\nabla T) = h_{int}(T_{ext} - T)$$


 $q = k \cdot \nabla T$ conductive heat flux vector $\left[\frac{W}{m^2}\right]$


 \imath normal vector of the boundary

 h_{int} heat transfer coefficient

Heat convective transfer coefficients (3)

Internal steel vessel





➤ Heat flux

$$-n \cdot (k\nabla T) = h_{i \ vav}(T_{ext} - T)$$

 $q = k \cdot \nabla T$ conductive heat flux vector $\left[\frac{W}{m^2}\right]$

n normal vector of the boundary

 h_{i_vap} heat transfer coefficient with helium vapor

> Heat flux


$$-n \cdot (k\nabla T) = h_{i \ lig}(T_{ext} - T)$$

 $q = k \cdot \nabla T$ conductive heat flux vector $\left[\frac{W}{m^2}\right]$

n normal vector of the boundary

 $h_{i \; liq}$ heat transfer coefficient with liquid helium

DAM (Double Aluminized Mylar)








Higher temperature gradient region


Simulation without DAM



The radiative net heat flux received by the shield maintained at 80K is very high and not sustainable by any commercial cold head

Simulation with DAM (1)


- > Ideal case:
 - separated DAM sheets: no contact points are considerated (only radiation between sheets)
 - ❖a single sheet with an effective emissivity taking in account the effect of 60 DAM sheets
 - Perfect insulation



The heat flux entering the external aluminum vessel, from 698.42 to 2.985 W.

Simulation with DAM (2)

>A more realistic model was analyzed in Matlab



• In addition to the radiative contribution, a further conductive term was considered throught the spacer (k=0.0012)

Cold Head


☐ In combination with an effective insulation system, radiative shields are maintained at a specified temperature by a "cold head".


☐ In this work the Pulse Tube Refrigerator with two refrigerating stages is used in order to reduce the temperature gradient in the cryostat.

Model of Cold head in Comsol

☐ Two copper plates (4.12 cm diameter and 2.06 cm diameter), simulating two refrigerant stages of a pulse tube, put in contact with two cryo-shields

- ☐ Thermal boundary conditions:
- Specified temperature
- ❖Specified inward heat flux





Boundary Condition

□ The imposed heat flux, to be removed by the refrigerating stage through each contact surface, was set as equal to the overall difference between the incoming and outgoing flux from the shield

Geometry with flat closures		
<u>Surfaces</u>	Radiative heat flux [W]	
External surface external steel vessel	-8.12	O_{TE80}
Internal surface external steel vessel	3.06	
External surface internal alu vessel	-3.06	
Internal surface internal alu vessel	0.011	QTF20

Thermal performance (1)

19.5

19

18

18

17

17


16.5


▼ 16.13

• Geometry with flat closures

Maximum Temperature	80.23 K
Minimum Temperature	77.46 K
Average Temperature	80 K

Internal Aluminum shield





Surface: Temperature (K)

80

79.5

79

78.5

77.5

▼ 77.465

Maximum Temperature	20.27 K
Minimum Temperature	16.13 K
Average Temperature	19.99 K



Thermal performance (2)

22.5

22

21.5


21


20.5

Imposed temperature at the cold head surfaces

Surface: Temperature (K)

Internal Aluminum shield





Maximum Temperature	82.57 K
Minimum Temperature	80 K
Average Temperature	82.36 K

Maximum Temperature	23.85 K
Minimum Temperature	20 K
Average Temperature	23.59 K




Zero-Boil Off System

Condensation inside
the vessel of helium
that could be
evaporated, eliminating
helium consumption.


□Single shield

□Two refrigerate stages (50 e 4,2 K)



Model of Cryostat


Geometry with three vessels



Results with cold head


Heat flux TF50	-6.36 [W]
Heat flux TF4.2	-0.44 [W]


Surface: Temperature (K)



Surface: Temperature (K)

Helium vessel





The temperature below 4.2K allows the helium vapor recondensation




Simulation with tie rods


□ For MRI machines, tie-rods are made of fiber glass because this material achieves a mechanical resistance near to theoretical resistance of the covalent bond.

□ Each vessel contains 4 tie-rods which fix it on the opposite one.

□ Provide a conductive way for heat among the vessels.

Temperature fields along tie rods for imposed heat flux (1)







Thermal field along fiber glass tie-rod inserted between esxternal and internal aluminum vessel

Temperature field along fiber glass tie-rod in contact with internal steel vessel containing liquid helium

Temperature fields along tie rods for imposed heat flux (2)



Thermal field on External Aluminum Vessel



Thermal field on External Steel Vessel

Discussion

□ Temperature value at the end of the tie-rod, in contact with the external steel, is lower than the average temperature of the vessel (equal to 293.1 K).

□For internal steel vessel this effect is not negligible since the temperature value at the contact points with tie-rods reaches a value of 5.79 K so the liquid helium evaporates very quickly


Conclusions (1)

- □ Preliminary results related to the description of thermal field in a cryostat for nuclear magnetic resonance imaging have been presented.
- Resulting heat flux entering in 80K cryo-shield without DAM's sheet is too high and not sustainable by any commercial cold head.
- □ Two boundary conditions have been analyzed to simulate the effect of the cold head.

Conclusions (2)

- □Zero-boil off system have been simulated with helium vessel maintained at 4K; resulting heat flux entering in cryo-shield and vessel wall is sustainable by cold head.
- ■With regard to tie rods, the choice of material is crucial to maintain the empty cavity and avoid the quench of magnet.

FUTURE DEVELOPMENTS



Acknowledgments

• The authors thank Prof. Francesco Paolo Branca for constructive comments and helpful suggestions and for making available the NMR tomography.